



## Lingua CHC

### Lingua Digital Infrared Charging Case



#### Description

The Lingua Charging Case can charge up to 64 Lingua infrared receivers at once. In just 2 hours, all receivers are fully charged.

The case has been designed for *frequent use and safe transportation*. It is built from durable, rugged materials and has several handles. As a result, it is easy and comfortable to move around. Finally, the cases may easily be stacked on top of one another.

#### Features

- Room for 64 receivers (includes status LED)
- Rapid charging
- Sturdy case for safe transport
- Onboard webserver
- Possibility to cascade Lingua CHC (via network and power)
- Easy updates of Lingua CHC and Lingua Receivers
- Factory reset button
- Lingua CHC status LED

#### Connectivity

- Factory reset button
- Lingua CHC status LED
- 2 Ethernet connections
- 2 Mains connection (for cascading)
- 64 receivers
- Connected to Lingua RX 6/12/40

## Certifications

Region	Certification
Europe	CE

## Specifications

Mechanical	
Material	Steel
Color	RAL 9011
Size (mm)	515 (w) x 275 (h) x 405 (d)
Weight empty (g)	12,500
Weight full (64 receivers) (g)	20,000
Electrical	
Mains voltage	~125V (60Hz) ~230V (50Hz)
Power consumption	300 W

All information copyright **Televic Conference**, 2016. Version 1.0, September 2016

—  
Leo Bekaertlaan 1 · 8870 Izegem · Belgium  
Tel. +32 51 30 30 45  
Fax +32 51 31 06 70  
E-mail: [conference@televic.com](mailto:conference@televic.com)  
Web: <http://www.televic-conference.com>  
*Televic reserves the right to change this document without notice.*